

Approved Compatibility List of Inverter Brands

Low voltage Residential Energy Storage Solution

Inverter brand	Inverter model	Inverter	Battery	Battery series	
		Protocol options	Protocol options	HLS-1X5/10/15/20K	HLR-1X5/10/15/20K
Haier	H1PL-1J3/3.6/5/6K-EU	Haier LV	INV-07	√	√
	H1PL-2J3/3.6/5/6K-EU	Haier LV	INV-07	√(CEI 0-21 listing)	√(CEI 0-21 listing)
NAHUI	N1PL-1M3K/3K6/4K/4K6/5K/6K, 1 phase	/	INV-09	√	√
Deye	SUN-3.6/5/6K-SG03LP1-EU, 1 phase	Default, 00	INV-04	√	√
	SUN-5/6/8/10/12K-SG04LP3-EU, 3 phase	Default, 00	INV-04	√	√
Solis	RHI-(3-6)K-48ES-5G 11A, 230V 1 phase	Haier LV	INV-07	√	√
	S5-EH1P(3-6)K-L 15A, 230V 1 phase	Haier LV	INV-07	√(CEI 0-21 listing)	√(CEI 0-21 listing)
	S6-EH1P(3-6)K-L, 230V 1 phase	Haier LV	INV-07	√	√
Megarevo	R3K/3K6/4K/4K6/5K/6KL1, 1 phase	/	INV-09	√	√
	R5K/6K/8K/10KLNA, split phase	/	INV-09	√	√
Afore	AF3K-6K-SL, 1 phase	Haier LV	Default	√	√
	AF1K-4.6KW-SL-O	Haier LV	Default	√	√
Goodwe	GW3648D/5048D-ES, 230V 1 phase	Default	INV-03	√	√
	EM:GW3048/5048-EM LV, 230V 1 phase	Default	INV-03	√	√
	S-BP:GW3600S/5000S-BP, 230V 1 phase	Default	INV-03	√	√
Luxpower	LUX-LB-US 12KW ,split phase	19	INV-10	√	√
	LXP3/3.6/4.6/6K, 1 phase	19	INV-10	√	√
Sacolar	M5000H-48BP	51	INV-02	√	√
	MHP series/ MHP 3000 series	51	INV-02	√	√
	MLP series/SP series	51	INV-02	√	√
Solark	Sol-Ark-5k-P,Sol-Ark-8k-P,Sol-Ark-12k-P,split phase	00	INV-04	√	√

High voltage Residential Energy Storage Solution

Inverter brand	Inverter model	Inverter	Battery	Battery series	
		Protocol options	Protocol options	HHS-1X5/10/15/20K	
Haier	H3PH-1J6/8/10K-EU	HaierHV	INV-07	√	
Goodwe	GW5/6/8/10KL-ET	Default	INV-03	√	
Deye	SUN-5K~20K-SG01HP3-EU-AM2	Default, 00	INV-04	√	
Solis	S6-EH3P(5-10)K-H-EU	HaierHV	INV-07	√	

